

Panasonic KX-TES824, KX-TA308, KX-TA616, KX-TA624, KX-TA30, KX-TA100, KX-TA200 Alcatel 4400		
Pbx	PC	
<b>Db9</b>	DB 9	DB 25
<b>2</b>	3	2
<b>3</b>	2	3
<b>4</b>	6	6
<b>5</b>	5	7
<b>6</b>	4	20
<b>7</b>	8	5
<b>8</b>	7	4

Panasonic KX-T336, XK-TD500		
Pbx	PC	
<b>Db 25</b>	DB 9	DB 25
<b>1</b>		1
<b>2</b>	2	3
<b>3</b>	3	2
<b>6</b>	4	20
<b>7</b>	5	7
<b>20</b>	6, 7, 8	5, 6, 4

Panasonic: BV9 KX-TD123211 KX- T336 KX-TD1232X		
Pbx	PC	
<b>DB25</b>	DB 9	DB 25
<b>1</b>		1
<b>2</b>	2	3
<b>3</b>	3	2
<b>4</b>	7	
<b>5, 6, 8</b>	4	20
<b>7</b>	5	7
<b>20</b>	1, 6, 8	5, 6, 8
<b>22</b>	9	

Panasonic: KX-T616, KX-T1232, KX-TD1232, KX-TD816, KXT-61610		
Pbx	PC	
<b>DB25</b>	DB 9	DB 25
<b>2</b>	2	3
<b>3</b>	3	2
<b>4</b>	7	4
<b>5, 6</b>	4	20
<b>7</b>	5	7
<b>20</b>	1, 6, 8	5, 6, 8

Samsung: SKP-56HX		
Pbx	PC	
<b>DB 9</b>	DB 9	DB 25
<b>2</b>	3	2
<b>3</b>	2	3
<b>4</b>	6	6
<b>5</b>	5	7
<b>6</b>	4	20
<b>7</b>	8	5
<b>8</b>	7	4

Samsung NX1232, NX 308, NX820		
Pbx	PC	
<b>DB 9</b>	DB 9	DB 25
<b>2</b>	3	2
<b>3</b>	2	3
<b>5</b>	5	7
<b>8</b>	4	20

Samsung SKP-816 H		
Pbx	PC	
<b>DB 25</b>	DB 9	DB 25
<b>2</b>	3	2
<b>3</b>	2	3
<b>4</b>	7	5
<b>6</b>	6	6
<b>7</b>	5	7
<b>20</b>	4	20

Samsung DCS y NX		
Pbx	PC	
<b>DB 25</b>	DB 9	DB 25
<b>2</b>	3	2
<b>3</b>	2	3
<b>7</b>	5	7
<b>20</b>	4	20

Siemens: HICOM 150 E		
Pbx	PC	
DB 25	DB 9	DB 25
2	2	3
3	3	2
4	8	5
5	7	4
6	4	20
7	5	7
8	1	8
20	6	6
22	9	22

Siemens: HICOM 130		
Pbx	PC	
DB 25	DB 9	DB 25
2	2	3
3	3	2
4	8	20
5	7	5
7	5	7

Siemens: HICOM 112, 118, 150, HIPATH 3350 OFFICE 150		
Pbx	PC	
DB 25	DB 9	DB 25
1		1
2	2	3
3	3	2
4	8	5
5	7	4
6	4	20
7	5	7
8	1	8
20	6	6
22	9	22

Lucent Technologies: Merlin Legend		
Pbx	PC	
RJ45	DB 25	DB 9
2	5, 6, 8	8, 6, 1
3	20	4
4	7	5
5	3	2
6	2	3

Lucent Technologies: Merlin Legend 511 A, partner acs, partner II, partner plus		
Pbx	PC	
RJ45	DB 25	DB 9
2	5, 6, 8	1, 6, 8
3	20	4
4	7	5
5	3	2
6	2	3

Mitel: SX-20, SX-200, GENERIC 1001, GL		
Pbx		PC
DB 9	DB 9	DB 25
1	1	8
2	2	3
3	3	2
4	4	20
5	5	7
6	6	6
7	7	4
8	8	5

NORTEL MERIDIAN OPCION 11, MERIDIAN 11 RELEASE 2255, RELEASE 2111, RELEASE 24, NORTSR O X 32 SMDR6, 4 X 16 FFC VER 4.0		
Pbx		PC
DB 25	DB 9	DB 25
1		1
2	3	2
3	2	3
4	7	4
5	8	5
6	6	6
7	5	7
20	4	20

### Comunicación de 2 pcs Serial a Serial

Bidireccional	
Pc	
Db 25	Db 25
1	11
2	10
3	8
4	9
8	3
9	4
10	2
11	1
12	15
15	12
18	18

Bidireccional	
Pc	
Db 25	Db 25
2	3
3	2
4	1, 6
5	5
6, 1	4
7	8
8	7

Unidireccional			
pc		Pc	
Db 9	Db 25	Db 9	Db 25
5	7	7	5
7	2	3	2
3	4	5	8
1, 6	6	20	4
2	3	2	3
8	5	4	7
4	20	6	1, 6

### Tabla de conversiones

Db 9	Db 25
1	8
2	3
3	2
4	20
5	7
6	6
7	4
8	5
9	22